

Multiple Power Outlet Racks



PROFESSIONAL P.A. SOUND SYSTEM PROFESSIONAL P.A. SOUND SYSTEM PROFESSIONAL P.A. SOUND SYSTEM PROFESSIONAL P.A.

MPR 1033DB



MPR 1030DL



SPECIFICATIONS	MPR-1033DB	MPR-1030DL
Instrument Type:	AC Outlet Multiple Power Rack	
AC Voltage Input Range:	180 - 300 Vac 50 Hz	
Display Monitor:	3 Digits Red LED AC Voltage Meter 100 - 300 V & 3 Digits Green LED AC Amp Meter 0 - 100 A	3 Digits Red LED AC Voltage Meter 100 - 300 V & 3 Digits Blue LED AC Amp Meter 0 - 100 A
Rear AC Outlet:	8 Outputs 3P 10 A 250 Vac	
Front AC Outlet:	2 Outputs 3P 10 A 250 Vac	2 Outputs 3P 10 A 250 Vac (Bypass)
Maximum Current Rating:	30 A	
Overload Protection:	Power Breaker 2P, Surge Suppressor by MOV	
Surge Suppressor by MOV:	Yes	
Noise Capacitor Filter:	Yes	
Power On Indicator:	Blue LED	
Front LED Light:	Front LED Light Bar 9 LED White Lamp (12 Vdc)	Front Pull Out LED Light Pipe 6 LED White Lamp (5 Vdc)
Select Level Front Light:	Off / On Switch & Dimmer	Low, Off, High
USB Charger:	2 USB Type-A Connector	
USB Power Supply:	5 V, 2 A max	
Rear Mounted Portable Gooseneck 5 Vdc Lamp:	USB Type-A Connector & On / Off Switch with Red LED Indicator	
AC Status Visual LED Indicators:	Ground Corrected, Phase Corrected, Fault Wiring	-
AC Wire Size / Length:	3 x 1.5 sq.mm. / 4 M	3 x 1.0 sq.mm. / 4 M
Dimensions: (WxHxD)	484 x 55 x 162 mm.	483 x 44 x 205 mm.
Net Weight:	3.28 kg (7.216 lbs)	2.60 kg (5.72 lbs)

FEATURE

USB CHARGER เมื่อป้อนไฟฟ้า 220 Vac 50 Hz จะมีแรงดันไฟฟ้า 5 Vdc ที่ Port USB Type-Aทันที ไม่ผ่านการควบคุมของ Power Breaker

MPR-1033DB



DIMMER LIGHT สามารถเลือกให้ไฟ LED Bar ทำงานได้ 3 สถานะ:

- หมุนวอลลุ่มในตำแหน่ง OFF "ปิดแสง"
- หมุนวอลลุ่มตามเข็มนาฬิกา "เพิ่มแสงสว่าง"
- หมุนวอลลุ่มมาจนสุด "เพิ่มสว่างมากที่สุด"



ด้านใต้เครื่อง

LED LAMP BAR แถบไฟ LED สีขาว 9 ดวง สามารถควบคุมเปิด-ปิด และปรับความสว่างได้ด้วยวอลลุ่มด้านหน้าเครื่อง

MPR-1030DL



LED LAMP PIPE กระบอกไฟ LED สีขาว 6 ดวง สามารถควบคุมเปิด-ปิด และปรับความสว่างได้ด้วยสวิตช์ด้านหน้าเครื่อง

SELECT LIGHT สามารถเลือกให้ไฟ LED PIPE ทำงานได้ 3 สถานะ:

- เลือกสวิตช์ไปไว้บนสุด "สว่างมาก"
- เลือกสวิตช์ไว้ตรงกลาง "ปิดแสง"
- เลือกสวิตช์ไปไว้ด้านล่างสุด "สว่างน้อย"