



# Mixing Amplifier

## Model : PM-1010U



### System Features

- ▶ The integral broadcasting power amplifier integrated MP3 player, FM tuner, partitioner (6 partitions) , pre-amplifier and power amplifier
- ▶ MP3/TUNER is subject to remote control, and it is possible to control the conversion between MP3/TUNER, selection of program, adjustment of volume, option repeat mode, and selection of EQ mode and so on by means of infrared remote control; and selection USB/SD
- ▶ Support FM, USB / SD
- ▶ 4 Mic inputs, 3 AUX inputs and 1 AUX output.
- ▶ Output , P1 (4-16 ohm)
- ▶ 6-zone output , 100V,70V
- ▶ Individual volume control and output level indication for each zone output
- ▶ Mute function for priority for Mic 1 input
- ▶ Treble and Bass control
- ▶ Built-in chime signal
- ▶ 5-unit LED Meter for monitoring volume output in each zone.
- ▶ Output short circuit protection and caution

### Specification

▶ Rated Output	500W
▶ Input sensitivity	MIC: 3.0 mV( $\pm 0.5$ mV) LINE: 300 mV( $\pm 50$ mV)
▶ Frequency response	20 Hz -20 kHz ( $\pm 3$ dB)
▶ Distortion	< 1% ( @ 1 kHz, 1/3 rated output voltage)
▶ Protection	AC fuse , DC voltage; overload; short-circuit , overload
▶ Temperature Control	Electrical auto fan (Start when over temperature)
▶ Power supply	AC110V-240V/50 Hz-60 Hz

#### Distributor

V.C.M. ELECTRONIC SOUND PROJECT LIMITED PARTNERSHIP  
No.20 Prapitak Rd. Wangburapapirom Pranakorn Bangkok 10200 THAILAND  
email:vcmaudio1@gmail.com  
Line@:vcmaudio

