

KSA-MP3 SERIES



SPECIFICATIONS	KSA-300MP3	KSA-500MP3
Connectors	2 Binding Posts	
Power Output	150W / 8Ω 250W / 4Ω	250W / 8Ω 450W / 4Ω
Mic Input:		
Type / Connectors	Balanced / 1/4" TRS	
Input Impedance	2.2kΩ	
Input Sensitivity @8Ω	-52dBu	
Frequency Response @0, -3dB	20Hz - 20kHz	
Hum & Noise	< -30dBu	
THD+N @1kHz	0.1%	
Maximum Level	-30dBu	
Aux Input:		
Type / Connectors	Unbalanced / RCA	
Input Impedance	47kΩ	
Input Sensitivity @8Ω	-15dBu	
Frequency Response @0, -2dB	20Hz - 20kHz	
Hum & Noise	< -35dBu	
THD+N @1kHz	0.1%	
Maximum Level	10dBu	
Subwoofer Out:		
Type / Connectors	Unbalanced / RCA	
Frequency Response	60Hz - 380Hz	
Shift Phase	0° - 180°	
Mic Tone Control:	3 Stage Bass, Mid and High	
Low	±12dB @60Hz Shelving	
Mid	±12dB @1kHz Peaking	
High	±12dB @12kHz Shelving	
Line Tone Control:	3 Stage Bass, Mid and High	
Low	±12dB @80Hz Shelving	
Mid	±12dB @1kHz Peaking	
High	±12dB @12kHz Shelving	
Echo Delay Time Control:	150 - 450ms	
FM Tuner Frequency:	87.5MHz - 108MHz	
Power Requirement:	220VAC 50Hz	
Power Consumption: Idle / Rate 4Ω	34W / 945W	70W / 1,580W
Dimensions: (WxHxD)	435x132x460mm	
Net Weight:	17.4kg(38.28lbs)	19.4kg(42.68lbs)

FEATURES

- เป็นเครื่องขยายเสียงสเตอริโอคาราโอเกะ
- KSA-300MP3 กำลังขยาย 150W+150W ที่ 8 โอห์ม 250W+250W ที่ 4 โอห์ม
- KSA-500MP3 กำลังขยาย 250W+250W ที่ 8 โอห์ม 450W+450W ที่ 4 โอห์ม
- มีชุดปรับแต่งเสียง กุ่ม-กลาง-แหลม
- มีเครื่องเล่น USB/SDHC/MP3/FM Radio/Bluetooth
- มี Digital Echo และระบบตัดเสียงร้องอัตโนมัติ เมื่อพูดไมค์
- มีช่องต่อ Subwoofer Out สามารถปรับความถี่และเฟสได้
- มีจุดเชื่อมต่อตู้ลำโพง 2 คู่

SYSTEM DIAGRAM



Note: 0dBu=0.775Vrms, 0dBV=1Vrms

All features & specifications subject to change without notice. © NPE Industry (Thailand) Co.,Ltd August 2018