

DPR-020 FM



SPECIFICATIONS	DPR-020FM
Input & Output Connector Type:	6.3mm Unbalanced TS Phone Jack
Input Impedance:	
MIC1, MIC 2	2kΩ Unbal., 4kΩ Bal.
AUX	10kΩ
Digital Player & Recorder	20kΩ
Frequency Response 0,-3dB:	
MIC	28Hz-18kHz
AUX	20Hz-47kHz
Digital Player & Recorder	10Hz-50kHz
Voltage Gain:	
MIC	56.7dB
AUX	17.5dB
Digital Player & Recorder	5.8dB
THD+N @0dBu 1kHz:	
MIC	<0.3%
AUX	<0.12%
Digital Player & Recorder	<0.11%
Hum & Noise:	
MIC	<-58.8dBu
AUX	<-75.7dBu
Digital Player & Recorder	<-82dBu
Max Input Voltage:	
MIC	25mVrms
AUX	2.5Vrms
Digital Player & Recorder	5.48Vrms
Output:	
Pre Output	9Vrms
Monitor	0.3+0.3Wrms @8Ω
Headphone	Cut Speaker Monitor
Voice Priority	OFF/ON
Output Selector	Monitor Speaker/Pre Out
Digital Player & Recorder MP3 With FM:	
Input Source	SD/MMC Card, USB Mp3, FM
Compatible up to	32Gb
Playing Format	MP3
Recording Format	MP3
Record On MP3	128kbps
FM Tuner	87.5-108MHz
Input/Output LED VU Display	-20,-15,-9,-6,-3,0,+3,+6 dB
Power Requirement	220Vac 50Hz
Power Consumption	15VA
Dimensions/Packing (WxHxD):	432x88x197mm./496x137x237mm.
Weight/Gross Weight:	3.6kg (7.92lbs)/4.5kg (9.9lbs)

Feature

- เครื่องเล่นและบันทึกเสียงไฟล์ MP3 ใช้กับ USB Drive & SD/MMC Card
- เครื่องรับวิทยุ FM 87.5-108MHz 0.05MHz/Step พร้อมแจ็กต่อสายอากาศภายนอก
- บันทึกเสียงสด (Real Time Recording) จากอนาล็อกอินพุตและแปลงเป็นไฟล์ MP3 ได้ทันที
- บันทึกเสียงเป็นระบบโมโนไฟล์ MP3 ระดับ 128Kbps
- ช่องใช้งานอนาล็อกอินพุต AUX 1 ช่อง และ MIC 2 ช่องพร้อมวอลลุ่มปรับแยกอิสระ
- สวิตซ์ Voice Priority ให้เวลาพูดไมค์แล้วตัดเสียง AUX อัตโนมัติ
- สวิตซ์และวอลลุ่ม Monitor ไว้ดังฟังเสียงออกก่อนปล่อยสัญญาณ Pre out ออกทางหูฟังหรือลำโพงภายในได้
- ไฟ VU LED แสดงระดับเอาต์พุต -20,-15,-9,-6,-3,0,+3,+6dB
- ไฟ PEAK แสดงระดับสัญญาณบันทึกเกินขนาด
- หน้าจอ LCD แสดงข้อมูลเพลงและสถานะการใช้งาน
- ขนาดแท่นมาตรฐาน 2U พร้อมปีกข้างคู่แบบถอดประกอบได้สำหรับยึดกับตู้ Rack มาตรฐาน

