



SS-1010/SS-1010R/SS-2010

Speaker Selector



# Speaker Selectors

TOA Speaker Selectors are designed to effectively select required speaker zones in a public address system and is ideal for small to medium-sized installation. Up to 10 speaker zones for paging and background music can be selected. For all models, in the situation where announcements have to be made to all zones, an All Call button can be selected to broadcast the message to all areas. For SS-1010 & SS-1010R previously selected BGM zones will be mute when paging is done to other zones. With the SS-2010, uninterrupted background music setup can be configured so that paging in one zone does not affect the background music in other zones.

## Features:

- DC 24 V operation
- LED indicator for each selector
- 1U 19" rack size
- 10 selectors for paging & background music for SS-1010R & SS-2010
- 1 selector for all call (paging)
- Protection against DC input overload and reversed DC polarity installation



## Specifications

Model	SS-1010 AS	SS-1010R AS	SS-2010 AS
Voltage Source	24V DC		
Current Consumption	0.4 A DC		0.6 A DC
Inputs	10 Inputs Zone 1 Emergency Override	10 Inputs BGM/Paging, 1 Link as Input/Output	10 Inputs BGM 10 Inputs Paging
Output	10 Outputs Zone each zone max. output 480W	10 Outputs with 3 wire R-H-C each zone max. output 480W	10 Outputs each zone max. output 480W at 100V line
Controls	Front	10 Zone Selectors, 1 All Zone Selector	10 BGM Selectors, 10 Paging Selectors 1 All Call Selector for All Paging
	Rear	1-10 Zone Controls In, All Zone Control In	1-10 Paging Controls In, All Paging Control In
Indicator LED	10 Zone Selector LEDs 1 All Zone LED	10 BGM Selector LEDs 10 Paging Selector LEDs 1 All Call LED	10 BGM Selector LEDs 10 Paging Selector LEDs 1 All Call LED
	Operating Temperature	0°C to +40°C	
Finish	Front Panel: Aluminum Hair Line, Etching Black Case: Steel Plate, Black		
Dimensions	482 (W) x 44 (H) x 320 (D) mm		
Weight	3.2kg		
Accessories	6P connectors (12pcs), 2P connector (1pc)		

