

PFX SERIES

POWER MIXER with EFFECT / USB / BLUETOOTH

NTS



SPECIFICATION

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- PHANTOM, PFL switch on all input
- Built in 99 program digital effect
- USB interface for MP3 input and playback with digital display
- BLUETOOTH function
- 7 band graphic EQ
- +48V phantom power supply

SPECIFICATION :

Power Output 200W x 2 @ 8Ω
 350W x 2 @ 4Ω
 Frequency Response 10Hz - 60KHz
 Distortion (THD & N) 0.01%
 Signal to Noise Ratio 112dB
 Equalization : High ± 15dB, 12kHz
 : Mid ± 15dB, 2.5kHz
 : Low ± 15dB, 80Hz

Mic Input Electronically balanced
 Gain Range +6dB to +60dB
 Line Input Electronically balanced
 Line Level Range +10dBu to -40dBu
 Max Output +22dBu balanced
 Aux Send Max Out +22dBu unbalanced
 Control Room Out +22dBu unbalanced

PFX-6

6 Mono input power mixer

PFX-8

8 Mono input power mixer