



# MUSIC

Professional Natural Music Sound.

model. MKL

เครื่องขยายเสียงเพาเวอร์มิกเซอร์ กำลังวัตต์สูง  
ทรานซิสเตอร์ มีลายน์แม่แมตซึ่งในตัว  
มีเครื่องเล่น USB บันทึกได้, Micro SD, Bluetooth และวิทยุในตัว



MKL-1500W

MKL-2000W

MKL-2500W

MKL-3000W

## SPECIFICATION

## POWER MIXER AMPLIFIER

|                          |                                                                                                                                                               |                                    |
|--------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------|
| TYPE.....                | PUBLIC ADDRESS MONO HIGH POWER MIXER AMPLIFIER Built-in MASTER LINE-MATCHING<br>FLEX LINE AMPLIFIER built-in USB RECORDABLE / Micro SD / FM TUNER / Bluetooth |                                    |
| INPUT.....               | 5 MIC / LINE with SELECTOR SW                                                                                                                                 | IMP. 600Ω / 47kΩ (1/4" PHONE JACK) |
| .....                    | 2 AUX with SELECTOR SW                                                                                                                                        | IMP. 47kΩ (RCA JACK)               |
| .....                    | 1 AUX / USB with SELECTOR SW                                                                                                                                  | IMP. 47kΩ (RCA JACK)               |
| INPUT CONTROL.....       | CHANNEL VOLUME CONTROL                                                                                                                                        |                                    |
| INPUT TONE CONTROL.....  | LOW ~ MID ~ HIGH +/-15dB                                                                                                                                      |                                    |
| INPUT FUNCTION.....      | CLIP LED & AUTO MUTE @CHANNEL                                                                                                                                 |                                    |
| .....                    | AUTO MUTE FUNCTION (SELECTED CH SOUND LEVEL HAVE REDUCED AUTOMATICALLY<br>WHEN NOT SELECTED CH SPEAK)                                                         |                                    |
| MASTER CONTROL.....      | MASTER VOLUME CONTROL                                                                                                                                         |                                    |
| MASTER TONE CONTROL..... | LOW ~ MID ~ HIGH +/-15dB                                                                                                                                      |                                    |
| MASTER FUNCTION.....     | HIGH PASS LF FILTER HORN SWITCH (250Hz CUT OFF)                                                                                                               |                                    |
| .....                    | INPUT OF POWERAMP PA IN (PHONE JACK), PRE OUT (PHONE JACK)                                                                                                    |                                    |
| .....                    | RELAY / RECORD OUT (PHONE JACK), SEND & RETURN (PHONE JACK) FOR EFFECT / GEQ                                                                                  |                                    |