

PM SERIES

POWER MIXER with EFFECT / USB / BLUETOOTH

NTS



SPECIFICATION

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- PFL switch on all input
- Built in 99 program digital effect
- USB interface for MP3 input and playback with digital display
- USB interface for connect mixer to PC
- BLUETOOTH function
- Recording function
- 5 band graphic EQ
- +48V phantom power supply

SPECIFICATION :

Power Output 120W x 2 @ 8Ω
..... 200W x 2 @ 4Ω
Input Sensitivity : Mic -50dB
: Line -40dB
Max Output 4V max
Frequency Response 20Hz - 20KHz

PM-5

5 Channel input power mixer
(3 Mono input & 1 Stereo input)

PM-7

7 Channel input power mixer
(5 Mono input & 1 Stereo input)

PM-9

9 Channel input power mixer
(7 Mono input & 1 Stereo input)

Distortion (THD & N) ≤ 0.05%
Signal to Noise Ratio ≥ 90dB
Equalization : High ± 15dB, 12KHz
: Mid ± 15dB, 2.5KHz
: Low ± 15dB, 80Hz