

PMR SERIES

POWER MIXER with EFFECT / USB / BLUETOOTH

NTS



SPECIFICATION

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- PAD switch
- Built in 99 program digital effect
- USB interface for MP3 input and playback with digital display
- USB interface for connect mixer to PC
- BLUETOOTH function
- Recording function
- 7+7 band graphic EQ
- +48V phantom power supply

PMR-1030

10 Channel input power mixer
(6 Mono input & 2 Stereo input)

PMR-1050

10 Channel input power mixer
(6 Mono input & 2 Stereo input)

SPECIFICATION :

PMR-1030

PMR-1050

Power Output	230W x 2 @ 8Ω	330W x 2 @ 8Ω
.....	300W x 2 @ 4Ω	500W x 2 @ 4Ω
Frequency Response	20Hz - 20KHz	
T.H.D.	0.005% / 0.004% A-weighted	
Signal to Noise Ratio	110dB / 112dB A-weighted	
Equalization : High	± 15dB, 12kHz	
: Mid	± 15dB, 3kHz	
: Low	± 15dB, 80Hz	
Size :	6U height / 10" depth	