

PA-120 Mixing Amplifier



Features

- 2 Mic Inputs , one has a priority function
- 1 Line Input
- 2- band EQ
- Built-in MP3 player support USB disk and Bluetooth
- There are 4-16 Ω , 70V, 100V three outputs modes, and 1 line output. The 100V has 2-section output with independent volume control.
- Compare with the analog amplifier, the same level Class-D amplifier can be more portable, which loses 60% weight, and reduces energy consumption for 40% at the same time. And this series has over protection, short circuit protection, input signal limit, output current over current limit, and other perfect protection

Technical Specification

MAX Output	120W
Output	4-16 Ω , 70V/100V
2 Band EQ	Bass : 100 HZ -6dB/-12dB Treble : 10 kHz +/- 12dB
Frequency Response (1% distortion @ Max Power)	80 Hz - 15 kHz \pm 3dB
THD (1 kHz)	\leq 1%
Inputs	Mic 1-2 : +45dB 2K Ω unbalanced Line : -7dB 10k Ω unbalanced
Power Supply	220V / 50Hz