

GBP-SERIES

POWER MIXER with EFFECT / USB / BLUETOOTH

NTS



GBP-SERIES

Stereo Power Mixer with Digital Effect / USB Input / BLUETOOTH Function

TECHNICAL SPECIFICATION

- insert point on mono input
- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- LOW CUT switch on mono input
- MUTE and SOLO switch on all input
- Built in 256 program digital effect
- USB interface for MP3 input and playback with digital display
- BLUETOOTH function
- 9 band graphic EQ
- +48V phantom power supply

GB-8P : Power Mixer 8 Channel

(4 Mono + 2 Stereo Input)

GB-12P : Power Mixer 12 Channel

(4 Mono + 4 Stereo Input)

GB-16P : Power Mixer 16 Channel

(8 Mono + 4 Stereo Input)

SPECIFICATION :

Power Output	300W x 2 @ 8Ω
.....	500W x 2 @ 4Ω
Frequency Response	20Hz - 20KHz
T.H.D.	0.005% / 0.004% A-weighted
Signal to Noise Ratio	110dB / 112dB A-weighted
EQ : HIGH	+/-15dB, 12KHz
: MID	+/-15dB, 2.5KHz
: LOW	+/-15dB, 80KHz