



### TN-390

Features :  
 Digital Display  
 AM : 522-1620kHz  
 FM Stereo : 87.5-108MHz  
 Auto search tuning and manual tuning  
 20 preset memories (FM 10 and AM 10)

## Specifications

FM Tuner :	
.....Frequency Range :	87.5-108MHz
.....Antenna Terminals :	75 ohm Unbalanced
.....30dB Sensitivity	<10 $\mu$ V
.....Frequency Response :	20Hz-15kHz +/-3dB
.....IF Rejection :	>80dB
.....Total Harmonic Distortion :	1%
.....Signal-to-noise Ratio :	>50dB
.....Stereo Separation 1kHz :	>40dB
AM Tuner :	
.....Frequency Range :	522-1620kHz
.....Antenna Terminal :	Loop Ant.
.....20dB Sensitivity :	<1mV
.....Signal-to-noise Ratio :	>35dB
Dimensions (WxHxD) :	
.....Exclude Mounting	432x78.5x280mm.
.....Include Mounting	483x80x284mm.
Power Requirement :	220Vac 50Hz 5VA
Weight :	4kg/8.8lbs

All features & specifications subject to change without notice.

© NPE Industry (Thailand) Co.,Ltd October 2004

### Natthapong Sales & Service Co.,Ltd.

#### Head Office :

119, 119/1 Assadang Rd., Wangburapapirhom, Bangkok 10200 Thailand.  
 Tel: 0-2623-8899, 0-2225-0094 (18 Line Auto)  
 Fax: 0-2226-4020 (local), 0-2225-2528 (int'l)

#### Zeer Rangsit Branch : G Floor

99 Moo 8 Phaholyothin Rd., Kukod, Lumlukka, Pathumthani 12130 Thailand.  
 Tel: 0-2992-7379 Fax: 0-2992-7380

http://www.myNPE.com, E-Mail: myNPE@myNPE.com  
 http://www.NPE.co.th, E-Mail: NPE@NPE.co.th

[www.myNPE.com](http://www.myNPE.com)