



MIXING AMPLIFIER

Model : PM-60MB

PRODUCT DESCRIPTION

This Compact USB/BT Mixing Amplifier provides 60 watts of output power with bluetooth , internal USB audio player power , and 5 inputs including 3 balanced MIC (MIC 1 has another port of 6.35 mm jack on front panel), 2 unbalanced AUX , each one has individual volume control.



FEATURES

- Mixer amplifier for paging and background music system
- Rated power 60W
- SMT circuit boards with high stable performance
- Built-in Bluetooth receiver and USB Player
- VU Meter (LED Display) show the signal
- 70V, 100V and low impedance 4/8 ohm speaker output
- Three balanced Mic input
- Mic 1(phone jack) with VOX priority and VOX level on front panel to reduce all signals.
- Mic 3 XLR type on rear panel with phantom power in MIC 1
- Two Aux Inputs , 1 phone and 1 RCA
- Mic 1-3, Aux 1-2 and master volume controls and bass/treble tone control
- Signal for short circuit protection, overload and high temp protection (AC Fuse, DC voltage overload) and peak current limiters



TECHNICAL SPECIFICATION

Power Supply	AC 220 - 240 V / 50-60Hz
Rated Power Output	60W
Inputs	3 Mic (Phone Jack x 1 , XLR x1 , XLR/AUX x 2 (PHONE,RCA)
Outputs	4-8Ω, 70V, 100V and COM
Frequency Response	60Hz - 18 kHz ±3dB
THD @ 1 kHz	less than 1% @ 1kHz, 1/3 rated power
S/N ratio	≥75 dB
Tone Control	BASS : 100 Hz (± 10dB) , TREBLE : 10 kHz (± 10 dB)
Dimensions	290(W)x260(D)x100(H)
Weight	5.5 kg.