

CM-1000M

Chime Microphone

with Music Player



Specifications :

CM-1000M

Microphone:

Design	46 cm Gooseneck with LED & XLR3-M
Type	Unidirectional Condenser Cartridge
Connector	XLR3-F (1 G, 2 +, 3 LED)
Sensitivity	-37 dBu
Frequency Response	70 Hz - 15 kHz 0, -3 dB
THD+N	< 0.1 %
Hum & Noise	< -90 dBu

Chime 4 Tone:

Talk On Frequency	440, 554, 659, 880 Hz
Talk Off Frequency	880, 659, 554, 440 Hz

MP3 Player:

Frequency Response	50 Hz - 20 kHz 0, -3 dB
THD	< 0.3 %
Bluetooth Device Name / Range	MIX-MP3 - BT / 10 m
PC USB Device Driver	Jieli BR21
MP3 USB Equalizer Mode	Natural, Rock, Pop, Classic, Jazz, Country

Output:

Connector	XLR3-M, Phones 1/8" TRS Jack
Mic / Chime Level	-10 dBu Balanced
Phones / Record Level	17 mW @ 16 Ω / 12 dBu @ 100 k Ω
Cable	1.5 m XLR-Female to 1/4" TRS Plug

Power:

Connector	DC Jack in $\varnothing$ 2 mm
Requirement	Adaptor 220 Vac to 15 Vac / 20 Vdc 300 mA
Consumption	3 W

Dimensions (W x H x D):

154 x 63 x 157 mm

Packing Dimension (W x H x D):

208 x 100 x 490 mm

Net Weight:

1.64 kg (3.61 lbs)

Gross Weight:

2.14 kg (4.71 lbs)

คุณสมบัติ

- เป็นไมค์ประเภทเสียงแบบตั้งโต๊ะ พร้อมเครื่องเล่นเสียง Bluetooth/PC/MP3 ในตัว
- ไมค์โครโฟนชนิดก้านอ่อนมีแสงสีแดงที่คอ ถอดเสียงได้ยาว 46 cm.
- มีสวิตซ์เปิด-ปิดไมค์พูดพร้อมเสียงระฆัง 4 โทน และตัดต่อเสียงเพลงอัตโนมัติ
- มีช่องต่อ Output แบบ Balance XLR และหูฟัง/Record ชนิด 1/8" TRS
- มีสวิตซ์เปิด-ปิด Output ปุ่มปรับความดังเสียงระฆัง, ไมค์, เพลง และหูฟังแยกอิสระ
- มีหม้อแปลงไฟภายนอก 1 อัน และสายสัญญาณยาว 1.5 เมตร 1 เส้น
- สามารถเปิดวิทยุได้ ด้วยการเชื่อมต่อเครื่องเล่นภายนอกโดยใช้ Bluetooth

Note: 0dBu=0.775Vrms, 0dBV=1Vrms