

KM-SERIES

STEREO MIXER with EFFECT / USB / BLUETOOTH

NTS



KM-SERIES

Stereo Mixer with Digital Effect / USB Input / BLUETOOTH Function

TECHNICAL SPECIFICATION

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- Peak LED on all input
- PHANTOM, PAD and MUTE switch on all input
- Built in 16 program digital multi-effect
- USB interface for MP3 input and playback with digital display
- BLUETOOTH function
- 7 band graphic EQ
- +48V phantom power supply

KM-8 : Stereo Mixer 8 Mono Input

KM-12 : Stereo Mixer 12 Mono Input

KM-16 : Stereo Mixer 16 Mono Input

SPECIFICATION :

Frequency Response	20Hz - 20KHz
T.H.D.	0.005% / 0.004% A-weighted
Signal to Noise Ratio	110dB / 112dB A-weighted
EQ : HIGH	+/-15dB, 12kHz
: MID	+/-15dB, 3kHz
: LOW	+/-15dB, 80Hz