

PKM SERIES

POWER MIXER with EFFECT / USB / BLUETOOTH

NTS



SPECIFICATION

- 3 band EQ on all input
- 1 Aux send for external effects and monitoring
- PHANTOM, PAD, SOLO and MUTE switch
- Built in 99 program digital effect
- USB interface for MP3 input and playback with digital display
- USB interface for connect mixer to PC
- BLUETOOTH function
- Recording function
- 7+7 band graphic EQ
- +48V phantom power supply

SPECIFICATION :

Power Output	300W x 2 @ 8Ω 500W x 2 @ 4Ω
Frequency Response	20Hz - 20KHz
T.H.D.	0.005% / 0.004% A-weighted
Signal to Noise Ratio	110dB / 112dB A-weighted
Equalization : High	± 15dB, 12kHz
: Mid	± 15dB, 3kHz
: Low	± 15dB, 80Hz