

TOP4 SERIES

POWER MIXER with EFFECT / USB / BLUETOOTH

NTS



SPECIFICATION

- 4 output power mixer with LPF switch and SUB FREQ adjustment
- 3 band EQ on all input
- 2 Aux send for external effects and monitoring
- PHANTOM, PAD, SOLO and MUTE switch
- Built in 24 program digital effect
- USB interface for MP3 input and playback with digital display
- USB interface for connect mixer to PC
- BLUETOOTH function
- Recording function
- 9+9 band graphic EQ
- Stereo output and mono output

TOP4-1040 / TOP4-1080

10 Channel input power mixer
(6 Mono input & 2 Stereo input)

TOP4-1240 / TOP4-1280

12 Channel input power mixer
(8 Mono input & 2 Stereo input)

TOP4-1640 / TOP4-1680

16 Channel input power mixer
(12 Mono input & 2 Stereo input)

SPECIFICATION : TOP4-1040 / TOP4-1240 / TOP4-1640

Power Output	270W x 4 @ 8Ω	535W x 4 @ 8Ω
.....	400W x 4 @ 4Ω	800W x 4 @ 4Ω
Frequency Response	20Hz - 20KHz	
T.H.D.	0.005% / 0.004% A-weighted	
Signal to Noise Ratio	110dB / 112dB A-weighted	
Equalization : High	± 15dB, 12kHz	
: Mid	± 15dB, 3kHz	
: Low	± 15dB, 80Hz	

TOP4-1080 / TOP4-1280 / TOP4-1680